

APPENDIX N

Referring to ~~[Fig. 7]~~ Figures 7A and 7B, although there is no stable condition where two devices drive the bus at the same time, conditions can arise because of propagation delay on the wires where one device, A 41, can start driving its part of the bus 44 while the bus is still being driven by another device, B 42 (already asserting a logical 1 on the bus). In a system using current drivers, when B 42 is driving the bus (before time 46), the value at points 44 and 45 is logical 1. If B 42 switches off at time 46 just when A 41 switches on, the additional drive by device A 41 causes the voltage at the output 44 of A 41 to drop briefly below the normal value. The voltage returns to its normal value at time 47 when the effect of device B 42 turning off is felt. The voltage at point 45 goes to logical 0 when device B 42 turns off, then drops at time 47 when the effect of device A 41 turning on is felt. Since the logical 1 driven by current from device A 41 is propagated irrespective of the previous value on the bus, the value on the bus is guaranteed to settle after one time of flight (t_f) delay, that is, the time it takes a signal to propagate from one end of the bus to the other. If a voltage drive was used (as in ECL wired-ORing), a logical 1 on the bus (from device B 42 being previously driven) would prevent the transition put out by

device A 41 being felt at the most remote part of the system, e.g., device 43, until the turnoff waveform from device B 42 reached device A 41 plus one time of flight delay, giving a worst case settling time of twice the time of flight delay.